Amendments to the Specification

Please replace the paragraph beginning on page 7, line 1, with the following rewritten paragraph:

--While any sequence is playing, the operator can single click on the print button **44** to initiate a printing operation. When the print button is depressed, the image frame corresponding to the last high resolution image is displayed in window **34**. The user can skip back to the previous high resolution image by single clinking on the back arrow **41**, or can rapidly move to earlier high resolution images by "clicking and holding" ~~back~~ forward arrow [[41]] **43**. Similarly, the user can skip forward to the next high resolution image by single clicking on the forward arrow **43**, or can rapidly move to later high resolution images by "clicking and holding" back arrow **41**. When the user double-clicks on the print button **44**, a print is produced from the high resolution still image data for this image frame on a color printer **47** such as an ink jet or laser printer, that is connected to the user's terminal or personal computer **33**.--

Please replace the paragraph beginning on page 7, line 13, with the following rewritten paragraph:

--The architecture of the digital motion/still camera **12** is illustrated in FIG. 3. The digital camera **12** produces digital image files that are recorded using a digital recorder **48**. The camera is powered by batteries **80** which connect to power supply **82**, which supplies power to the camera circuits depicted in FIG. 3. The digital camera **12** includes a zoom lens **51** having zoom and focus motor drives **53** and an adjustable aperture (not shown). The user composes the scene using the electronic viewfinder **72** and the zoom lens control buttons (not shown) of the user controls [[66]] **90**, and then depresses a record button (not shown) to begin capture of a motion/still image sequence. The zoom lens **51** focuses light from a subject **14** (see FIG 1) on an image sensor **50**, for example, a single-chip interline color CCD image sensor using the well-known Bayer color filter pattern. The image sensor may be an interline format sensor having 1280 columns x 960 rows of active pixels. The image sensor **50** is

controlled by timing generator/clock drivers **70**. The zoom and focus motors **53** and the clock drivers **70** are controlled by control signals supplied by a control microprocessor **68**. The analog output signal from the image sensor **50** is amplified and converted to digital data by the analog signal processing (ASP) and analog-to-digital (A/D) converter circuit **52**. The camera **12** also includes a microphone **56** and an audio A/D converter **58** for providing a digital audio signal to digital processor [[68]] **66**.

Please replace the paragraph beginning on page 8, line 18, with the following rewritten paragraph:

-- The outputs of the full resolution buffer memory **60** and the multi-frame reduced resolution buffer memory **62** are coupled to a multiplexer switch **64** which provides an input to ~~control microprocessor 68~~ digital processor **66**. The digital audio data from audio A/D **58** is also input to ~~control microprocessor 68~~ digital processor **66**. The processed image and audio data is coupled to a digital recorder **48** which stores the digital image files. The digital recorder can use write-once or erasable CD or DVD optical disks. Alternatively, the digital recorder can use other digital storage technologies, such as magnetic hard drives, magnetic tape, optical tape, or solid-state memory.

Please replace the **PARTS LIST** beginning on page 13, with the following rewritten **PARTS LIST**:

--**PARTS LIST**

10	capture step x
12	motion/still camera x
14	photographic subject x
16	digitize step x
18	compress video step x
20	full resolution image x
22	generate sequence x
24	storage step x

26	writable medium x
28	display, review and print step x
30	user interface display x
31	CRT x
32	array of index images x
33	personal computer x
34	playback window x
35	mouse x
36	stereo speakers x
37	operating system x
38	start window x.
39	application software x
40	stop window x
41	back arrow x
42	play button x
43	forward arrow x
44	print button x
45	keyboard x
47	color printer x
48	digital recorder x
50	image sensor x
51	zoom lens x
52	video A/D converter x
53	zoom and focus motor drives x
54	2:1 subsampler x
56	microphone x
58	audio A/D converter x
60	full resolution buffer memory x
62	reduced resolution buffer memory x
64	multiplexer switch x
66	~~user controls x~~ <u>digital processor</u>
68	control microprocessor x
70	timing circuit x
72	electronic viewfinder x
74	video output signal x
80	batteries x

82	power supply x
90	user controls
102	high resolution frame x
104	low resolution frame x
112	processing time for high resolution frame x
114	processing time for low resolution frame x
200	MPEG-2 bitstream x
202	I frame x
204	B frame x
206	P frame x
210	high resolution compressed image files x
220	pointer x--